

Troubleshooting Guide

NO FOOD Alarm - If re-priming of the pump delivery set is required, it is advisable to disconnect the enteral adapter from the patient's feeding tube while re-priming. Is bag of pump Refill bag, re-prime delivery set and resume feeding. delivery set empty? T NO T Manually prime tubing by turning bag upside down, gently squeezing lower half of bag while pinching the teal colored tubing just below NO ▶ the "O" drop symbol. Hold this position until Has air been all air is removed from bag and tubing. Is air present in removed from the tubing? bag of pump Press and hold the PRIME key to move delivery set? the air in the tubing past pump delivery set cassette and resume feeding. NOTE: If your pump is equipped with an auto prime option, refer to the Operator's Manual for details. , NO T Let formula sit for 10-15 minutes before preparing pump delivery set Is formula blenderized for feeding. If foam is present in tubing, flush by priming pump delivery or aggressively mixed? set either manually or with the pump and resume feeding. T NO T Remove tubing from pump and manually prime tubing by turning bag upside down, gently squeezing lower half of bag while pinching the teal colored tubing just below the drop symbol. Hold this position Are air bubbles trapped until all air has passed through the teal segment of the tubing. inside the cassette? If alarm continues, contact Moog Customer NO I Service at 800.970.2337 for assistance.

LOAD SET Alarm		and the second s
Is door closed securely?	NO/UNSURE	Turn pump off. Unload and reload delivery set cassette. Make sure door is closed securely, then turn pump back on.
Is door cracked or tab on side of door broken?	YED:	If alarm continues, contact Moog Customer Service at 800.970.2337 to order a new door.
	No 🗠	If alarm continues, contact Moog Customer Service at 800.970.2337 for assistance.

ER01 - ER99 Alarms		
Was pump door open	:∉YES/UNSURE ▶	Turn pump off. Unload and reload delivery set cassette. Make sure door is closed securely, then turn pump back on.
while pump was turned on or while running?	No ▶	If alarm continues, contact Moog Customer Service at 800.970.2337 for assistance.



Speak live with a Moog Clinical Representative for pump questions and troubleshooting guidance 24 hours per day, 7 days per week.

Clinical & Customer Support 800.970.2337
Visit infinityfeedingpump.com for additional information



NO FLOW IN or NO FLOW OUT Alarm NO FLOW IN: Occlusion between delivery set and pump. NO FLOW OUT: Occlusion between pump and patient. Is delivery set tubing Check delivery set for pinches or kinks in tubing and resume feeding. pinched or kinked? V NO V Contact Moog Customer Service at Is tab on inside of door broken? 800.970.2337 to order a new door. T NO T Clean pressure sensor area with a cotton swab, soft cloth, Is pressure sensor region of or dampened sponge; or wash entire pump under running NO. cassette receptacle clean? water. Do not use abrasive materials or harsh chemicals. Contact Moog Customer Service at 800.970.2337 to return pump for service Disconnect feeding set from patient. Press the RUN key. If pump delivers food without alarm, check patient's feeding tube for obstruction. If alarm continues, remove set from pump, gently massage the " $\mathring{\mathbb{Q}}$ " Are there visible signs drop symbol, then manually prime set until occlusion is cleared and of damage to pressure formula advances through tubing. Replace set and resume feeding. sensors area? NO P If unable to advance formula through tubing or alarm continues, contact Moog Customer Service at 800.970.2337 to return pump for assistance.

Charging Problems		
Is A/C adapter charger plugged into walk outlet and pump properly?	NO/UNSURE ▶	Check connections for both wall plug and pump adapter. Green indicator light on charger wall plug should be illuminated and pump display should have plug symbol with scrolling bars between E and F of fuel gauge. When pump is fully charged, bars will stop scrolling.
Y YES Y		
Is wall outlet functioning properly?	NO/UNSURE	Plug another device into outlet to verify outlet is functioning properly.
The Free President Control of the President C		
Does charger adapter appear to have any damage?	WSD -	Contact Moog Customer Service at 800.970.2337 to order a new charger
▼ NO ▼	1	
Does charger port appear to have any damage including bent or missing pins?	(F)	Contact Moog Customer Service at 800,970.2337 to return pump for service.
▼ NO ▼		
Is Battery Symbol and E and F of fuel gauge flashing?	YES D	Contact Moog Customer Service at 800.970.2337 to return pump for service.

*Note: Do not use the **PRIME** key to troubleshoot or resolve these alarms.

